

Controlling Multiple Vi305 DVRs from a Vi-K1

Applies to: Vi305, Vi-k1

Menu configuration

- ♦ To enable multiple unit control you need to set a unit address for the Vi305's, each unit needs a different address: 1 (master), 2, 3 etc
- ♦ To set the address you need too select Menu, then using the arrow keys select Configuration menu, then select Multi unit configuration. Select a unique address and select the number of linked units.

Control

- ♦ Press and hold "LIVE" key then press "1" key. The Vi-K1 will now be addressing unit 1.
- ♦ Press and hold "LIVE" key then press "2" key. The Vi-K1 will now be addressing unit 2.
- ♦ Press and hold "LIVE" key then press "3" key. The Vi-K1 will now be addressing unit 3.
- ♦ Up to 10 DVR's can be controlled from a Vi-K1
- ♦ Once you have selected the Vi305 that you want control, use the keypad as normal.

Cabling

- ♦ Connect the units together following the configuration drawing.
- ♦ The input to the Vi305 is via the main keyboard input pins 1 & 2
- ♦ The output from the Vi-K1 is via the out port pins 1 & 2

